

ANNUNCIATION PANELS

Visual Alarm and Voice Annunciation Panel

Salient Features :-

- Six potential free contact input for six events.
- At each event custom set message is displayed and prerecorded announcement is activated.
- Event messages can be edited by connecting IBM keyboard directly to the display.
- RS485 output for repeater.
- 2000 characters can be saved in memory.



Synopsys Tech Pvt. Ltd.

A-001, Fressia CHS LTD, Baburao Ranade Marg, Off. L.M. Road, Behind Bank of India, Dahisar West,
Mumbai-400068. Tel. 022-28904500/6800/6500 Email :- info@synopsystech.com

Technical Specifications:-

- Operating Voltage : 230 V AC
- LED matrix : 7*90 with 3mm LED.
- LED color : Red
- No. of events : six
- Number of messages : six + one(default when no event)
- Number of sounds : six
- Power consumption : 15Watts
- Screen Size : 2" * 18"
- Working temperature : 0 to 50 degree C
- Construction : Metal Enclosure wall mounted
- Size : 22" X 4" X 8"

Synopsys Tech Pvt. Ltd.

A-001, Fressia CHS LTD, Baburao Ranade Marg, Off. L.M. Road, Behind Bank of India, Dahisar West, Mumbai-400068. Tel. 022-28904500/6800/6500 Email :- info@synopsystech.com